



## Radio Programming

Page #	1	Page #	2	Page #	3
Ch. #	Channel Name	Ch. #	Channel Name	Ch. #	Channel Name
1	Asbestos	1	Mech Zone 1	1	Project 1
2	Carpentry	2	Mech Zone 2	2	Project 2
3	Roofing	3	Mech Zone 3	3	Project 3
4	Paint / Sigh Shop	4	Mech Zone 4	4	Project 4
5	Access Control	5	Utility Services	5	Project 5
6	Heavy Construction	6	Chill Water	6	Project 6
7	Preventative Maint	7	Elec Dist	7	Project 7
8	Materials Mgmt	8	Elevators	8	Project 8
9	Electrical Shop	9	465.1000	9	Project 9
10	Plumbing Shop	10	All Call	10	Project 10
11	Landscape	11	All Call	11	Project 11
12	Recycling	12	All Call	12	Project 12
13	Building Service	13	All Call	13	Project 13
14	Service Support	14	All Call	14	Project 14
15	Silent / Dispatch	15	Silent / Dispatch	15	Project 15
16	All Call	16	All Call	16	All Call

## Radio Buttons

- 1) Orange Button: **Private Call to CONTROL**
- 2) Long Press (1 to 2sec): **Contacts List**
- 3) **PTT** (Push to Talk)
- 4) Long Press (1 to 2sec): **Backlight ON/OFF**
- 5) Long Press (1 to 2sec): **Keypad Lock/Unlock**
- 6) P1: **PAGE Menu**
- 7) P2: **Manual Dial**



Figure 1: Motorola XPR-6550

## How to:

### Change Pages

- Press the “**P1**” button (*Figure1, #6*)
- Then press the “*Right or Left Arrows*” until the **Page** desired is displayed on the screen.
- Press “**OK**”
- Press the “**Home/Back**” button

### Call Control/Dispatch Directly

- Press the Orange Button (*Figure 1, #1*)
- Press the PTT (*Figure 1, #3*) and speak
- Or go to **Ch 15** in **Page 1 or 2** and press the **PTT** button and speak

### Manual Dial a Radio

- Press the “**P2**” button (*Figure1, #7*)
- Enter the ID of the radio using the number pad
- Press the **PTT** and speak
- Or press “**OK**” twice to send an Alert.

### Add a new contact

- Press the “**Menu**” button
- Select contacts by pressing “**OK**”
- Press the “**Left**” arrow twice
- Press “**OK**”
- Enter the Radio ID (e.g. 451)
- Press “**OK**”

### Edit or Delete a contact

- Press the “**Menu**” button
- Select contacts by pressing “**OK**”
- Use the **Left** or **Right** arrows to navigate to the desired contact
- Press “**OK**”
- Use the arrow keys to select the desired option  
(e.g. *Delete entry, Edit Name, Edit Number*)